

HD Dome Network Camera WV-SF135 Dome Network Camera WV-SF132



HD/1,280 x 960 H.264 Dome Network Camera with 2x Extra Zoom (WV-SF135) VGA/640 x 480 H.264 Dome Network Camera (wv-sF132)

Key Features

- 720p HD images up to 30 fps (WV-SF135)
- 1.3 Megapixel high sensitivity MOS Sensor (WV-SF135)
- 0.32 Megapixel high sensitivity MOS Sensor (WV-SF132)
- Multiple H.264 (High profile) streams and JPEG streams ensure simultaneous real time monitoring and high resolution recording by "UniPhier®", Panasonic's proprietary System LSI platform.
- Full frame (Up to 30 fps) transmission at 1,280 x 960 image size (WV-SF135)
- Full frame (Up to 30 fps) transmission at VGA (640 x 480) image size (WV-SF132)
- ABS (Adaptive Black Stretch) technologies deliver wider dynamic range compared with conventional cameras.
- High sensitivity with Day & Night (Electrical) function: 0.8 lx (Color), 0.6 lx (B/W) at F2.2 (WV-SF135) 2.0 lx (Color), 1.3 lx (B/W) at F2.9 (WV-SF132)
- VIQS (Variable Image Quality on Specified area) technology allows the designated area to retain higher image quality while the excluded area will have a decreased image quality, which enables to use lower image file size and bit rate.
- Digital Noise Reduction: 3D-DNR ensures noise reduction in various conditions.
- · Progressive scan ensures clear images with less motion blur and no tearing even when the subject is moving.
- Superior color reproduction by primary (RGB) color filter
- Electronic sensitivity enhancement: Auto (Up to 16x) / OFF (WV-SF135) Auto (Up to 8x) / OFF (WV-SF132)
- 2x extra zoom under VGA resolution (WV-SF135)
- 2x, 4x digital zoom controlled by browser
- Selectable light control modes: Indoor scene (50 Hz) / Indoor scene (60 Hz) / ELC (maximum exposure time) Indoor scene (50 Hz/60Hz): Flicker caused by fluorescent lightning will be automatically compensated. ELC (maximum exposure time): The lightning control will be
 - automatically performed by adjusting shutter speed in the range of ELC.
- VMD (Video Motion Detection) with 4 programmable detection areas, 15 steps sensitivity level and 10 steps detection size

- Face detection function detects the position of human face and the information is sent by XML or video stream.
- Meta data for VMD works with the WJ-ND400 playback VMD
- Privacy Zone can mask up to 2 private areas, such as house windows and entrances/exits.
- Camera title display: Up to 20 alphanumeric characters on the browser
- Alarm sources including VMD and Panasonic alarm command can trigger actions such as FTP image transfer, E-mail notification, Indication on browser, and Panasonic alarm protocol output.
- JPEG Image compression ratio can be changed by alarm so that higher quality image can be provided.
- Prioritized stream control: One of the video streams can be prioritized when multiple recorders or client PCs are accessing the camera so that the recorder or the client PC can maintain the frame rate.
- H.264 max. bit rate/client and Total bit rate control allows flexible network traffic management. Frame rate priority mode controls bit rate and compression ratio to provide the specified frame rate.
- Internet mode: H.264 images can be transmitted over HTTP protocol.
- Multi-language: English / Italian / French / German / Spanish / Russian / Chinese / Japanese
- IPv4/IPv6 protocol supported
- Supports SSL, DDNS (viewnetcam, RFC2136)
- Still images (JPEG) can be viewed on mobile phones via Internet.
- · Onvif compliant model
- Low profile design for discrete installation
- Wide coverage

WV-SF135 Horizontal: 104°, Vertical: 85° WV-SF132 Horizontal: 68°, Vertical: 53°

Standard Accessories

- Installation Guide · Important Safety Instructions. • CD-ROM*1 ...1 pc. • Code Label*2 · Lens adjuster.
- The followings are for installation.
- Installation Template Label.
- *1 The CD-ROM contains the operating instructions and different kinds of tool software programs.

 *2 This label may be required for network management.
 The network administrator shall retain the code label.


Specifications

TV Systen	1		NTSC PAL	
Camera	Image Sensor		WV-SF135: 1/3 type MOS image Sensor	
			WV-SF132: 1/5 type MOS image Sensor	
	Effective P	ixels	WV-SF135: Approx. 1.3 megapixels	
			WV-SF132: Approx. 0.32 megapixels	
	Scanning Mode		Progressive	
	Scanning Area		WV-SF135: 4.8 mm (H) x 3.6 mm (V) (3/16" (H) x 5/32" (V))	
			WV-SF132: 2.69 mm (H) x 2.01 mm (V) (1/8" (H) x 1/16" (V))	
	Minimum Illumination		WV-SF135:	
			Color: 0.8 lx (F2.2, Auto slow shutter: Off (1/30 s), Gain: On(High)) 0.05 lx (F2.2, Auto slow shutter: Max. 16/30 s, Gain: On(High)) BW: 0.6 lx (F2.2, Auto slow shutter: Off (1/30 s), Gain: On(High)) 0.04 lx (F2.2, Auto slow shutter: Max. 16/30 s,Gain: On(High))	
			WV-SF132: Color: 2.0 lx (F2.9, Auto slow shutter: Max. 8/30 s, AGC: High)	
	White Balance		0.3 lx (F2.9, Auto slow shutter: Max. 8/30 s, AGC: High) ** BW: 1.3 lx (F2.9, Auto slow shutter: Max. 8/30 s, AGC: High)	
			0.16 lx (F2.9, Auto slow shutter: Max. 8/30 s, AGC: High) *	
			AWC (2,000 ~ 10,000 K), ATW1 (2,700 ~ 6,000 K), ATW2 (2,000 ~ 6,000 F	
	Light Control Mode		Indoor scene (50 Hz / 60 Hz) / ELC	
	ELC		1/30, 3/100, 3/120, 2/100, 2/120, 1/100, 1/120, 1/250, 1/500, 1/1,000	
			1/2,000, 1/4,000, 1/8,000 (WV-SF132), 1/10,000 (WV-SF135)	
	Day & Night (Electrical)		OFF / AUTO	
	Digital Noise Reduction		High / Low	
	Face Detection		ON / OFF (with the XML notification setting)	
	Adaptive Black Stretch		ON / OFF	
	AGC		ON (LOW, MID, HIGH) / OFF	
	Auto Slow Shutter		WV-SF135: Off(1/30s), Max. 2/30 s, Max. 4/30s, Max. 6/30s,	
	Video Motion Detection		Max. 10/30s, Max. 16/30s	
			WV-SF132: Off(1/30s), Max. 2/30 s, Max. 3/30s, Max. 4/30s,	
			Max. 8/30s Max. 2/30 s, Max. 3/30s, Max. 4/30s,	
			ON / OFF, 4 areas available	
	Privacy Zone		ON / OFF (up to 2 zones available)	
			ON / OFF	
	VIQS Camera title		Up to 20 characters (alphanumeric characters, marks), ON / OF	
Lens			1.95 mm	
Lens	Focal Length		WV-SF135: 1x Extra Zoom:2x (under VGA resolution)	
	Zoom Ratio		WV-SF133: 1X EXITA 20011.2X (under VGA resolution)	
	Manifestore Amendmen Datio			
			1 : 2.2 (WV-SF135) 1:2.9 (WV-SF132)	
	Adjusting Angle		Ceiling Installation Horizonatal: -20 ° to +20 ° Vertical: -20 ° to +90	
	Angular Field of View		Wall Installation Horizonatal: -80 ° to +80 ° Vertical: -90 ° to +20 WV-SF135: Horizontal: 104 °, Vertical: 85 °	
	Angular Field of View		WV-SF132: Horizontal: 104°, Vertical: 63° WV-SF132: Horizontal: 68°, Vertical: 53°	
Browser	Supported OS		Microsoft® Windows® 7,	
GUI	*2 *3		Microsoft® Windows Vista®,	
GOI				
	Supported Browser		Microsoft® Windows® XP SP3 Windows® Internet Explorer® 9.0 (32 bit),	
	Cupported Browser		Windows® Internet Explorer® 8.0 (32 bit),	
			Windows® Internet Explorer® 7.0 (32 bit),	
			Microsoft® Internet Explorer® 6.0 SP3	
Network	Network IF		10Base-T / 100Base-TX, RJ-45 connector	
	Image		WV-SF135: H.264: 1,280 x 960 / VGA (640 x 480) / QVGA (320 x 240), up to 30 fi	
	Resolution		JPEG (MJPEG): 1,280 x 960 / VGA (640 x 480) /QVGA (320 x 240), up to 30 fps	
	110001011011	[0]	WV-SF132: H.264: VGA (640 x 480) / QVGA (320 x 240), up to 30 fps	
			JPEG: VGA (640 x 480) / QVGA (320 x 240), up to 30 fp:	
		Aspect ratio:		
		[16 : 9]	H.264: 1280 x 720 / 640 x 360 / 320 x 180, up to 30 fps	
		[10.0]	JPEG: 1280 / 720 / 640 x 360 / 320 x 180, up to 30 fps	
			WV-SF132	
			H.264: 640 x 360 / 320 x 180, up to 30 fps	
		Eromo D-1-	JPEG: 640 x 360 / 320 x 180, up to 30 fps	
			1/3/5/7.5/10/15/20/30 fps 1/3/5/7.5/10/12/15/20/30 fp	
		DIL nate/Client	64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 1,536 / 2,048 / 3,072	
		l	4,096 / 8,192* kbps *H.264 mode only (WV-SF135)	
			LOW / NORMAL / FINE	
	IDEC		UNICAST / MULTICAST	
	JPEG		0 SUPER FINE / 1 FINE / 2 / 3 / 4 / 5 NORMAL / 6 / 7 / 8 / 9 LOW (10 steps: 0-	
	(MJPEG)		PULL / PUSH	
	Irancemis	sion Interval	0.1 fps - 30 fps (JPEG frame rate will be restricted when displa	
			both JPEG and H.264 images)	
	Bandwidth Control		64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 2,048 / 4,096 /	
	Supported Protocol		8,192 kbps / Unlimited	
			Pv6: TCP/IP, UDP/IP, HTTP, HTTPS, RTP, FTP, SMTP, DNS,	
			NTP, SNMP, DHCPv6	
			IPv4: TCP/IP, UDP/IP, HTTP, HTTPS, RTSP, RTP, RTP/RTCP,	
			FTP, SMTP, DHCP, DNS, DDNS, NTP, SNMP, UPnP	
	FTP Client		Alarm image transmission, FTP periodic transmission	
	Multi-screen		Up to 16 camera images can be displayed simultaneously on	
			multi-screen. (Including the camera itself)	
	Maximum Concurrent		14 (Depends on network conditions)	
	iviaximum	Concurrent	14 (Depends on network conditions)	
	Access Nu		14 (Depends of Hetwork conditions)	
	Access Nu			


TV Syster	m	NTSC	PAL
Alarm	Alarm Source	VMD, Command alarm	
	Alarm Actions	E-mail notification,Indication on browser, FTP image transfer,	
		Panasonic protocol output	
	Schedule	VMD	
General	Power Source	PoE (IEEE802.3af compliant)	
	Power Consumption	WV-SF135: PoE 48 V: 54 mA (Class1 device)	
		WV-SF132: PoE 48 V: 46 mA (Class1 device)	
	Ambient Operating	0 °C ~ +40 °C (32 °F ~ 104 °F),	
	Temperature/Humidity	Less than 90 % (no condensation)	
	Dimensions	ø100 mm x 47 mm (H) (ø3-15/16" x 5-3/4" (H))	
	Mass (approx.)	200 g (0.44 lbs.)	
	Finish	Main Body: ABS resin, Sail White	
		Dome Section: Clear Polycarbonate Besin	

- $^{\star}2$ Transmission for 2 streams can be individually set in the same compression method.
- $^{\star}3$ Refer to "Notes on Windows Vista® / Windows® 7" on the provided CD-ROM for further information about system requirements for a PC and precautions when using Microsoft® Windows® 7 or Microsoft® Windows Vista®.
- *4 When using IPv6 for communication, use Microsoft Windows 7 or Microsoft Windows Vista.

Part Names and Functions



Appearance



Trademarks and registered trademarks

- Microsoft, and Windows are registered trademarks of Microsoft Corporation in the U.S. and other countries.
- iPad, iPhone and iPod touch are registered trademarks of Apple Inc.
 ONVIF and the ONVIF logo are trademarks of ONVIF Inc.
- UniPhier is a registered trademark of Panasonic Corporation.

 "Super Dynamic", "SDII", "SDII", "SD5", "SD5Link", "I-PRO" and "I-PRO SmartHD" logos are trademarks or registered trademarks of Panasonic Corporation.

- Safety Precaution: carefully read the operating instructions and installation manual before using this product.
 Panasonic can not be responsible for network performance and/or other manufacturer products that
- reside on the network.
 - All TV pictures are simulated.
 - Masses and dimensions are approximate.
 - Specifications are subject to change without notice.
 - These products may be subject to export control regulations.
 - All product pictures are NTSC models.

DISTRIBUTED BY:

Mobile Terminal Compatibility iPad, iPhone, iPod touch

